

1,2-trans-DCE 1000 Sensorix

Electrochemical Gas Sensor for trans-1,2-Dichloroethylene
Only with Pyrolyzer unit


sensors made in germany

3-electrode sensor with EPROM for industrial safety applications

Class leading stability | Highly selective | Fast response | Very stable baseline

Performance Characteristics / PSDS	
Measurement Range	0 – 1000 ppm
Maximum Range	1000 ppm
Sensitivity	40 ± 20 nA/ppm
Response Time (T ₉₀)	≤ 120 s at 3 min gas exposure
Baseline (in clean air)	< ± 100 nA
Baseline (in clean air) (at midpoint sensitivity)	< ± 2.5 ppm
Lower Detectable Limit (LDL)	10 ppm
Alarm 1	200 ppm
Linearity	< 5% of full scale
Repeatability	< 3%
Product Safety Datasheet (PSDS)	acid electrolyte

Operating Conditions	
Temperature Range	-20°C to +40°C
Humidity Range	15% to 90% r.h. non-condensing
Pressure Range	800 – 1200 hPa
Bias Voltage	190 mV
Sensor warm-up time (of sensors with short circuit plug)	10 min
Recommended Orientation	sensor front pointing downwards or sideways

Sensorix PN: AN123S11 Compatible to OEM PN: 9602-9600	
<p>Compatible with Satellite XT transmitters according to the "Satellix Compatibility Declaration"</p> <p>Insert short circuit plug (jumper) in S and R (Remove before installation)</p> <p>IMPORTANT NOTE: Connection should be made via PCB sockets only. Soldering to pins will render your warranty void.</p> <p>All dimensions in mm (± 0.2 mm)</p> <p>Weight: ~7.0 g</p>	<p>Dimensions</p>  <p>Female Socket IEC 60130-9 7 POL (KV 71)</p>

Lifetime	
Long Term Output Drift	< 3% per months
Expected Operating Life	> 24 months in air
Recommended Storage conditions	5 – 20°C in sealed container

Performance and lifetime data are based on conditions at 20°C, 40 ... 60 % r.h. and ambient pressure.

SAFETY NOTE
This sensor is designed to be used in safety critical applications. The sensor is compatible with the self-test functionality of the Satellite XT Gas Detector Transmitter. In addition to this electrical diagnostic, Sensorix recommends that the function of the sensor is confirmed by exposure to a suitable test gas (bump check) regularly according to national and local regulations. Failure to carry out such tests may jeopardize the safety of people and property.



1,2-trans-DCE 1000 Satellix

Electrochemical Gas Sensor for trans-1,2-Dichloroethylene

Only with Pyrolyzer unit

sensors made in germany

Cross Sensitivity & Filter	
Gas concentration	Reading after 5 min
Ammonia 100 ppm	0 ppm
Carbon Dioxide 5000 ppm	0 ppm
Carbon Monoxide 100 ppm	0 ppm
Chlorine 5 ppm	0 ppm
Hydrocarbons (saturated) 1%	0 ppm
Hydrocarbons (unsaturated) 1%	0 ppm
Hydrogen Bromide 5 ppm	15 ppm
Nitrogen Dioxide 8 ppm	12 ppm
Sulphur Dioxide 20 ppm	25 ppm
Chemical Filter	None

Signals below LDL as well as negative readings will be displayed as zero.

IMPORTANT NOTE:

Interference factors may differ from sensor to sensor, with changing ambient conditions and with lifetime. It is not advisable to calibrate with interference gases. This table does not claim to be complete. The sensor may also be sensitive to other gases.

Temperature performance

Temperature dependence is compensated with microprocessor.

Poisoning

Sensorix cells are designed for operation in a wide range of environments and harsh conditions. However, it is important that exposure to high concentrations of solvent vapors is avoided, both during storage, fitting into instruments, and operation. When using sensors with printed circuit boards (PCBs), degreasing agents should be used before the sensor is fitted.

Recycling

At the end of the product's life, do not dispose of any electronic sensor, component, or instrument in the domestic waste, but contact the vendor or Sensorix for disposal instructions. Sensorix will take back sensors for professional recycling.

Every effort has been made to ensure the accuracy of this document at the time of printing. In accordance with the company's policy of continued product improvement Sensorix GmbH reserves the right to make product changes without notice. No liability is accepted for any consequential losses, injury or damage resulting from the use of this document or from any omissions or errors herein. The data is given for guidance only. It does not constitute a specification or an offer for sale. The products are always subject to a program of improvement and testing which may result in some changes in the characteristics quoted. As the products may be used by the client in circumstances beyond the knowledge and control of Sensorix GmbH, we cannot give any warranty as to the relevance of these particulars to an application. It is the clients' responsibility to carry out the necessary tests to determine the usefulness of the products and to ensure their safety of operation in a particular application.

Characteristics on this data sheet outline the performance of newly supplied sensors.

