

# AsH3 1 zero H2 Satellix LDL sensorix

Electrochemical Gas Sensor for Arsine

sensors made in germany

3-electrode sensor with EPROM for industrial safety applications in the presence of H2  
 Class leading stability | Highly selective | Fast response | Very stable baseline

Performance Characteristics / PSDS	
Measurement Range	0 – 1 ppm
Maximum Range	10 ppm
Sensitivity	600 ± 200 nA/ppm
Response Time (T <sub>90</sub> )	≤ 60 s at 2 min gas exposure
Baseline (in clean air)	< ± 3 nA
Baseline (in clean air) (at midpoint sensitivity)	< ± 0.005 ppm
Lower Detectable Limit (LDL)	0.01 ppm
Alarm 1	0.05 ppm
Linearity	< 5% of full scale
Repeatability	< 2%
Product Safety Datasheet (PSDS)	organic gel electrolyte

Operating Conditions	
Temperature Range	-20°C to +40°C
Humidity Range	15% to 90% r.h. non-condensing
Pressure Range	800 – 1200 hPa
Bias Voltage	no
Sensor warm-up time (of sensors with short circuit plug)	5 s
Recommended Orientation	sensor front pointing downwards or sideways

Sensorix PN: AN232S17 Compatible to OEM PN: 9602-6003	
<p>Compatible with Satellix XT transmitters according to the "Satellix Compatibility Declaration"</p> <p>Insert short circuit plug (jumper) in S and R (Remove before installation)</p> <p><b>IMPORTANT NOTE:</b> Connection should be made via PCB sockets only. Soldering to pins will render your warranty void.</p> <p>All dimensions in mm (± 0.2 mm)</p> <p>Weight: ~7.0 g</p>	<p><b>Dimensions</b></p> <p>Female Socket IEC 60130-9 7 POL (KV 71)</p>

Lifetime	
Long Term Output Drift	< 5% per month
Expected Operating Life	> 18 months in air
Recommended Storage conditions	5 – 20°C in sealed container

Performance and lifetime data are based on conditions at 20°C, 40 ... 60 % r.h. and ambient pressure.

**SAFETY NOTE**  
 This sensor is designed to be used in safety critical applications. The sensor is compatible with the self-test functionality of the Satellix XT Gas Detector Transmitter. In addition to this electrical diagnostic, Sensorix recommends that the function of the sensor is confirmed by exposure to a suitable test gas (bump check) regularly according to national and local regulations. Failure to carry out such tests may jeopardize the safety of people and property.



Cross Sensitivity & Filter	
Gas concentration	Reading after 5 min
Ammonia 20 ppm	0 ppm
Carbon Dioxide 5000 ppm	0 ppm
Carbon Monoxide 100 ppm	0 ppm
Hydrocarbons (saturated) 1%	0 ppm
Hydrogen 3000 ppm	0 ppm
Hydrogen 50%	0 ppm
Hydrogen Chloride 5 ppm	0.1 ppm*
Hydrogen Cyanide 5 ppm	1 ppm
Hydrogen Fluoride 5 ppm	0 ppm
Hydrogen Sulfide 20 ppm	0 ppm*
Isopropanol 600 ppm	0 ppm
Phosphine 1 ppm	1.2 ppm
Silane 5 ppm	0 ppm
Sulphur Dioxide 2 ppm	0 ppm*
Chemical Filter	Yes

\* Cross sensitivity depends upon filter status and will increase when filter is depleted.

Signals below LDL as well as negative readings will be displayed as zero.

#### IMPORTANT NOTE:

Interference factors may differ from sensor to sensor, with changing ambient conditions and with lifetime. It is not advisable to calibrate with interference gases. This table does not claim to be complete. The sensor may also be sensitive to other gases.

#### Temperature performance

Temperature dependence is compensated with microprocessor.

#### Poisoning

Sensorix cells are designed for operation in a wide range of environments and harsh conditions. However, it is important that exposure to high concentrations of solvent vapors is avoided, both during storage, fitting into instruments, and operation. When using sensors with printed circuit boards (PCBs), degreasing agents should be used before the sensor is fitted.

#### Recycling

At the end of the product's life, do not dispose of any electronic sensor, component, or instrument in the domestic waste, but contact the vendor or Sensorix for disposal instructions. Sensorix will take back sensors for professional recycling.

Every effort has been made to ensure the accuracy of this document at the time of printing. In accordance with the company's policy of continued product improvement Sensorix GmbH reserves the right to make product changes without notice. No liability is accepted for any consequential losses, injury or damage resulting from the use of this document or from any omissions or errors herein. The data is given for guidance only. It does not constitute a specification or an offer for sale. The products are always subject to a program of improvement and testing which may result in some changes in the characteristics quoted. As the products may be used by the client in circumstances beyond the knowledge and control of Sensorix GmbH, we cannot give any warranty as to the relevance of these particulars to an application. It is the clients' responsibility to carry out the necessary tests to determine the usefulness of the products and to ensure their safety of operation in a particular application.

Characteristics on this data sheet outline the performance of newly supplied sensors.

